
Email: info@coax-connectors.com



PRODUCT DATASHEET

MICRO BNC STRAIGHT CRIMP / CRIMP JACK 67-054-B66-FB1






4	CRIMP SLEEVE		BRASS			NICKEL	
3	INSULATOR		PTFE		N/A		
2	CENTRE CONTACT	BER	BERYLLIUM COPF		GOLD		
1	BODY		BRASS		NICKEL		
ITEM	DESCRIPTION		MATERIAL		PLATING		
A4	SHEET 1 OF 1		DIMENSIONS ARE IN MILLIMETRES				
REVISION: A01			NAME	SIGNATURE		DATE	
		DRAWN	BS			15/06/2018	
ISSUE	: 1	CHK'D	I.G.			15/10/2018	
6-8 COLNE ROAD, TWICKENHAM, MIDDLESEX.		APPV'D					
		THE INFORMATION IS GIVEN AS AN INDICATION ONLY AND IS SUBJECT TO CHANGE WITHOUT NOTICE. IN THE CONTINUAL GOAL TO IMPROVE OUR PRODUCTS, WE RESERVE THE RIGHT TO MAKE ANY MODIFICATIONS NECESSARY WITHOUT PRIOR					

Suitable for Cables:

(FB) Belden 1505A, Draka 0.8/3.7 A/F, Image 720, Bryant BD SD50A, Percon VK6, Conducfil 14472,

Stripping Dimensions



a = 4.0 mm [0.1575"]b = 8.0 mm [0.3150"]c = 16.0 mm [0.6299"]d = 12.0 mm [0.4724"]

* CUT FOIL TO DIM. "b"

Assembly Procedure: AP001

Tooling

Centre Contact: SQ 1.07 [0.0421"] A/F Tool No: 96-HTS-77

Crimp Sleeve: Hex 6.48 [0.255"] A/F Tool No: 96-HTS-77

Extraction: Not Applicable Alignment Tool: Not Applicable

Environmental Specification

Operating Temp: -55 to +155 Deg C.

IP Rating (Mated): IP 64

Electrical Specification Mechanical Specification

Impedance: 75 Ohm Contact Retention: 10 N min Cable Retention: 150 N min Frequency: 0-12 GHz

Dielectric W/V: 1000 Veff Mating cycles: 500 Insulation res: 10000 M-Ohm Weight: 5.06 g

Connector Interface



Tel: +44(0)20 8538 9090

THIS DOCUMENT IS THE PROPERTY OF COAX CONNECTORS LTD. REPRODUCTION OR COMMUNICATION IN ANY FORM TO A THIRD PARTY IS PROHIBITED WITHOUT PRIOR WRITTEN CONSENT

Fax: +44(0)20 8538 9890